



## SHOWERSTAR™

### SHOWER SENSOR TIMER + APP

ShowerStar™ is one of the highest impact and lowest-cost **water and energy efficiency** measures available, encouraging people to take shorter showers on a daily basis. A patent pending, simple DIY retrofit product that mounts onto an existing shower pipe or shower-head and automatically detects when a shower starts.

Once the sensor detects the shower has started, a timer starts decrementing. Customisable themes with visual alerts are provided at the start, half-time, full-time and overtime. The default theme is "Traffic Light" which indicates water flow detected, timer started and timer finished. There are more and less intrusive themes to drive behaviour change with different types of users.

The product is powered via a long life rechargeable battery with a USB type C port for charging from a standard USB 5VDC charger. The battery only needs to be recharged approximately every ~8-12 months depending on use and configuration\*.

Works with any type of water heater including electric storage, heat pump, gas and thermal storage and is complementary with other efficiency measures such as low-flow showerheads.

### CONFIGURATION AND MONITORING

The App connects via Bluetooth and is available in iOS and Android versions. The App enables device provisioning, configuration and monitoring.

### INSTALLATION

DIY installation onto a shower pipe (rigid or flexible, straight or corrugated) or directly onto a shower-head. Installation takes <2 minutes. First mount the mount bracket using supplied cable ties, then slide the product into the mounting cradle to complete the installation. No plumbing or electrical connection required.

### PORTAL

ShowerStars can be configured to upload non-personally identifiable usage data from each device to a cloud based Portal. This enables program managers to view and verify program device installation, data and persistence to inform program design and water heater load flex programs.

## FEATURES



## ELECTRICAL

### FOR INDOOR USE ONLY

Battery	1000mAh 3.7V Lipo Recharge every ~8-12 months* *Assumes 4 showers / day and subject to alert configuration
Charging	5VDC USB Charger
Communications	Bluetooth Low Energy™
App OS Support	iOS™ + Android™
Estimated Product Life	8-10 years

## PHYSICAL

Operating Temp	32° to 113° F   0° to 45° C
Storage Temp	14° to 140° F   -10° to 60° C
IP Rating	55
L x W x H	3.27" x 1.8" x 0.9"
	83mm x 45mm x 23mm
Weight	2.3 ounces   65 grams



## WARRANTY

1-year limited warranty

## APPROVALS

FCC (US) Part 15.247  
CE - EMC (EN IEC61326)  
RED ETSI EN 310 489-1, EN 301 489-17,  
ETSI EN 300 328, EN IEC 62311:



RCM, RoHS, Prop65



Battery (UL1642, UL2054, IEC62133, CB, CE, RoHS, UN38.3, REACH)



## FOR INDOOR USE ONLY.

**WATER RESISTANT, DO NOT IMMERSE FULLY IN WATER.**

## ORDERING

**TG168 ShowerStar Shower Sensor Timer**

## LEGAL

© 2024 TouchGrid Pty Ltd. All rights reserved.  
Designed in Australia.

© 2024 TouchGrid Pty Ltd. All rights reserved.  
TouchGrid and ShowerStar are registered trademarks of TouchGrid Pty Ltd. All other trademarks are the property of their respective owners. Patents Pending.